

12-27-99

Express Mail No.EL517007050US

Attorney's Docket No. NC29176

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

Box Patent Application
Assistant Commissioner for Patents
Washington, D.C. 20231

NEW APPLICATION TRANSMITTAL

Transmitted herewith for filing is the patent application of

Inventor(s): Qizheng Gu

WARNING: Patent must be applied for in the name(s) of all of the actual inventor(s). 37 CFR 1.41(a) and 1.53(b).

For (title): CDMA RECEIVER

CERTIFICATION UNDER 37 CFR 1.10

I hereby certify that this New Application Transmittal and the documents referred to as enclosed therein are being deposited with the United States Postal Service on this date, December 23, 1999, in an envelope as "Express Mail Post Office to Addressee" Mailing Label Number EL517007050UIS, addressed to the: Assistant Commissioner for Patents, Washington, D.C. 20231.

Veronica E. Cameau
(type or print name of person mailing paper)

Veronica E. Cameau
Signature of person mailing paper

NOTE: Each paper or fee referred to as enclosed herein has the number of the "Express Mail" mailing label placed thereon prior to mailing. 37 CFR 1.10(b).

WARNING: Certificate of mailing (first class) or facsimile transmission procedures of 37 CFR 1.8 cannot be used to obtain a date of mailing or transmission for this correspondence.

1. Type of Application

This new application is for a(n)

(check one applicable item below)

☒ Original (nonprovisional)

☐ Design

☐ Plant

WARNING: Do not use this transmittal for a completion in the U.S. of an International Application under 35 U.S.C. 371(c)(4), unless the International Application is being filed as a divisional, continuation or continuation-in-part application.

WARNING: Do not use this transmittal for the filing of a provisional application.

NOTE: If one of the following 3 items apply, then complete and attach **ADDED PAGES FOR NEW APPLICATION TRANSMITTAL WHERE BENEFIT OF A PRIOR U.S. APPLICATION CLAIMED** and a **NOTIFICATION IN PARENT APPLICATION OF THE FILING OF THIS CONTINUATION APPLICATION**.

☐ Divisional.

☐ Continuation.

☐ Continuation-in-part (C-I-P).

2. Benefit of Prior U.S. Application(s) (35 U.S.C. 119(e), 120, or 121)

NOTE: If the new application being transmitted is a divisional, continuation or a continuation-in-part of a parent case, or where the parent case is an International Application which designated the U.S., or benefit of a prior provisional application is claimed, then check the following item and complete and attach **ADDED PAGES FOR NEW APPLICATION TRANSMITTAL WHERE BENEFIT OF PRIOR U.S. APPLICATION(S) CLAIMED**.

WARNING: If an application claims the benefit of the filing date of an earlier filed application under 35 U.S.C. 120, 121 or 365(c), the 20-year term of that application will be based upon the filing date of the earliest U.S. application that the application makes reference to under 35 U.S.C. 120, 121 or 365(c). [35 U.S.C. 154(a)(2) does not take into account, for the determination of the patent term, any application on which priority is claimed under 35 U.S.C. 119, 365(a) or 365(b).] For a c-i-p application, applicant should review whether any claim in the patent that will issue is supported by an earlier application and, if not, the applicant should consider canceling the reference to the earlier filed application. The term of a patent is not based on a claim-by-claim approach. See Notice of April 14, 1995, 60 Fed. Reg. 20,195, at 20,205.

WARNING: When the last day of pendency of a provisional application falls on a Saturday, Sunday, or Federal holiday within the District of Columbia, any nonprovisional application claiming benefit of the provisional application must be filed prior to the Saturday, Sunday, or Federal holiday within the District of Columbia. See 37 C.F.R. § 1.79(a)(3).

☐ The new application being transmitted claims the benefit of prior U.S. application(s). Enclosed are **ADDED PAGES FOR NEW APPLICATION TRANSMITTAL WHERE BENEFIT OF PRIOR U.S. APPLICATION(S) CLAIMED**.

3. Papers Enclosed That Are Required for Filing Date under 37 C.F.R. 1.53(b) (Regular) or 37 C.F.R. 1.153 (Design) Application

 14 Pages of specification

 5 Pages of claims

 1 Page of Abstract

 9 Sheets of drawing

☐ formal

☒ informal

WARNING: DO NOT submit original drawings. A high quality copy of the drawings should be supplied when filing a patent application. The drawings that are submitted to the Office must be on strong, white, smooth, and non-shiny paper and meet the standards according to § 1.84. If corrections to the drawings are necessary, they should be made to the original drawing and a high-quality copy of the corrected original drawing then submitted to the Office. Only one copy is required or desired. Comments on proposed new 37 CFR 1.84. Notice of March 9, 1988 (1990 O.G. 57-92).

NOTE "Identifying indicia, if provided, should include the application number or the title of the invention, inventor's name, docket number (if any), and the name and telephone number of a person to call if the Office is unable to match the drawings to the proper application. This information should be placed on the back of each sheet of drawing a minimum distance of 1.5 cm (5/8 inch) down from the top of the page." 37 C.F.R. 1.84(c).

(complete the following, if applicable)

- ☐ The enclosed drawing(s) are photograph(s), and there is also attached a "PETITION TO ACCEPT PHOTOGRAPH(S) AS DRAWING(S)." 37 C.F.R. 1.84(b).

4. Additional papers enclosed

- ☐ Preliminary Amendment
☐ Information Disclosure Statement (37 C.F.R. 1.98)
☐ Form PTO-1449
☐ Citations
☐ Declaration of Biological Deposit
☐ Submission of "Sequence Listing," computer readable copy and/or amendment pertaining thereto for biotechnology invention containing nucleotide and/or amino acid sequence.
☐ Authorization of Attorney(s) to Accept and Follow Instructions from Representative
☐ Special Comments
☒ Other Return Postcard

5. Declaration or oath

- ☐ Enclosed
Executed by

(check all applicable boxes)

- ☐ inventor(s).
☐ legal representative of inventor(s). 37 CFR 1.42 or 1.43.
☐ joint inventor or person showing a proprietary interest on behalf of inventor who refused to sign or cannot be reached.
☐ This is the petition required by 37 CFR 1.47 and the statement required by 37 CFR 1.47 is also attached. See item 13 below for fee.

- ☒ Not Enclosed.

WARNING: Where the filing is a completion in the U.S. of an International Application, but where a declaration is not available, or where the completion of the U.S. application contains subject matter in addition to the International Application, the application may be treated as a continuation or continuation-in-part, as the case may be, utilizing ADDED PAGE FOR NEW APPLICATION TRANSMITTAL WHERE BENEFIT OF PRIOR U.S. APPLICATION CLAIMED.

- ☐ Application is made by a person authorized under 37 CFR 1.41(c) on behalf of **all** the above named inventor(s).

[The declaration or oath, along with the surcharge required by 37 CFR 1.16(e) can be filed subsequently.]

NOTE: It is important that all the correct inventor(s) are named for filing under 37 CFR 1.41(c) and 1.53(b).

- ☐ Showing that the filing is authorized.
[not required unless called in question. 37 CFR 1.41(d)]

6. Inventorship Statement

WARNING: If the named inventors are each not the inventors of all the claims an explanation, including the ownership of the various claims at the time the last claimed invention was made, should be submitted.

The inventorship for all the claims in this application are:

- ☒ The same.

or

- ☐ Not the same. An explanation, including the ownership of the various claims at the time the last claimed invention was made,
☐ is submitted.
☐ will be submitted.

7. Language

NOTE: An application including a signed oath or declaration may be filed in a language other than English. A verified English translation of the non-English language application and the processing fee of \$130.00 required by 37 CFR 1.17(k) is required to be filed with the application, or within such time as may be set by the Office. 37 CFR 1.52(d).

NOTE: A non-English oath or declaration in the form provided or approved by the PTO need not be translated. 37 CFR 1.69(b).

- ☒ English
☐ Non-English
☐ The attached translation is a verified translation. 37 CFR 1.52(d).

8. Assignment

- ☒ An assignment of the invention to Nokia Mobile Phones Limited
☐ is attached. A separate ☐ "COVER SHEET FOR ASSIGNMENT (DOCUMENT) ACCOMPANYING NEW PATENT APPLICATION" or ☐ FORM PTO 1595 is also attached.
☒ will follow.

NOTE: "If an assignment is submitted with a new application, send two separate letters—one for the application and one for the assignment." Notice of May 4, 1990 (1114 O.G. 77-78).

WARNING: A newly executed "CERTIFICATE UNDER 37 CFR 3.73(b)" must be filed when a continuation-in-part application is filed by an assignee. Notice of April 30, 1993, 1150 O.G. 62-64.

9. Certified Copy

Certified copy(ies) of application(s)

Country	Appln. no.	Filed
---------	------------	-------

Country	Appln. no.	Filed
---------	------------	-------

Country	Appln. no.	Filed
---------	------------	-------

from which priority is claimed

- ☐ is (are) attached.
☐ will follow.

NOTE: The foreign application forming the basis for the claim for priority must be referred to in the oath or declaration. 37 CFR 1.55(a) and 1.63.

NOTE: This item is for any foreign priority for which the application being filed directly relates. If any parent U.S. application or International Application from which this application claims benefit under 35 U.S.C. 120 is itself entitled to priority from a prior foreign application, then complete item 18 on the ADDED PAGES FOR NEW APPLICATION TRANSMITTAL WHERE BENEFIT OF PRIOR U.S. APPLICATION(S) CLAIMED.

10. Fee Calculation (37 C.F.R. 1.16)

- A. ☒ Regular application

CLAIMS AS FILED			
Number Filed	Number Extra	Rate	Basic Fee
			37 C.F.R. 1.16(a)
			\$760.00
Total Claims			
[37 CFR 1.16(c)] 2020 = 0	0	x \$18.00	0
Independent Claims [37 CFR 1.16(b)]			
4-3 = 1	1	x \$78.00	78.00
Multiple dependent claim(s), if any			
[37 CFR 1.16(d)]	0	+ \$260.00	0

- ☐ Amendment cancelling extra claims is enclosed.
☐ Amendment deleting multiple-dependencies is enclosed.
☐ Fee for extra claims is not being paid at this time.

NOTE: If the fees for extra claims are not paid on filing they must be paid or the claims cancelled by amendment, prior to the expiration of the time period set for response by the Patent and Trademark Office in any notice of fee deficiency. 37 CFR 1.16(d).

Filing Fee Calculation

\$838.00

- B. ☐ Design application
[\$310.00—37 CFR 1.16(f)]

Filing Fee Calculation \$

- C. ☐ Plant application
[\$480.00—37 CFR 1.16(g)]

Filing Fee Calculation \$

11. Small Entity Statement(s)

- ☐ Verified Statement(s) that this is a filing by a small entity under 37 CFR 1.9 and 1.27 is (are) attached.

WARNING: *Status as a small entity in one application or patent does not affect any other application or patent, including applications or patents which are directly or indirectly dependent upon the application or patent in which the status has been established. A nonprovisional application claiming benefit under 35 U.S.C. 119(e), 120, 121 or 365(c) of a prior application may rely on a verified statement filed in the prior application if the nonprovisional application includes a reference to a verified statement in the prior application or includes a copy of the verified statement filed in the prior application if status as a small entity is still proper and desired.* 37 C.F.R. § 1.28(a).

(complete the following, if applicable)

- ☐ Status as a small entity was claimed in prior application.
_____/_____, was filed on _____, from which
benefit is being claimed for this application under:

35 U.S.C. ☐ 119(e),

☐ 120,

☐ 121,

☐ 365(c),

and which status as a small entity is still proper and desired.

- ☐ A copy of the verified statement in the prior application is included.

Filing Fee Calculation (50% of A, B or C above)

\$ _____

NOTE: Any excess of the full fee paid will be refunded if a verified statement and a refund request are filed within 2 months of the date of timely payment of a full fee. The two-month period is not extendible under § 1.136, 37 CFR 1.28(a).

12. Request for International-Type Search [37 C.F.R. 1.104(d)]

(complete, if applicable)

- ☐ Please prepare an international-type search report for this application at the time when national examination on the merits takes place.

13. Fee Payment Being Made at This Time

☐ Not Enclosed

☐ No filing fee is to be paid at this time.
(This and the surcharge required by 37 C.F.R. 1.18(e) can be paid subsequently).

☒ Enclosed

☒ Filing fee \$838.00

☐ Recording assignment
[\$40.00; 37 C.F.R. 1.21(h)]
(See attached "COVER SHEET FOR ASSIGNMENT
ACCOMPANYING NEW APPLICATION").

☐ Petition fee for filing by other than all the inventors or
person on behalf of the inventor where inventor refused
to sign or cannot be reached
[\$130.00; 37 C.F.R. 1.47 and 1.17(h)]

☐ For processing an application with a specification
in a non-English language
[\$130.00; 37 C.F.R. 1.52(d) and 1.17(k)]

☐ Processing and retention fee
[\$130.00; 37 C.F.R. 1.53(d) and 1.21(l)]

☐ Fee for international-type search report
[\$40.00; 37 C.F.R. 1.21(e)]

NOTE: 37 CFR 1.21(l) establishes a fee for processing and retaining any application that is abandoned for failing to complete the application pursuant to 37 CFR 1.53(d) and this, as well as the changes to 37 CFR 1.53 and 1.78, indicates that in order to obtain the benefit of a prior U.S. application, either the basic filing fee must be paid, or the processing and retention fee of § 1.21(l) must be paid, within 1 year from notification under § 53(d).

Total fees enclosed

\$838.00

14. Method of Payment of Fees

☐ Check in the amount of \$ _____

☒ Charge Account No. 50-0270 in the amount of \$838.00

A duplicate of this transmittal is attached.

NOTE: Fees should be itemized in such a manner that it is clear for which purpose the fees are paid. 37 CFR 1.22(b).

15. Authorization to Charge Additional Fees

WARNING: If no fees are to be paid on filing, the following items should not be completed.

WARNING: Accurately count claims, especially multiple dependent claims, to avoid unexpected high charges, if extra claim charges are authorized.

- ☒ The Commissioner is hereby authorized to charge the following additional fees by this paper and during the entire pendency of this application to Account No. 50-0270.

☒ 37 C.F.R. 1.16(a), (f) or (g) (filing fees)

☒ 37 C.F.R. 1.16(b), (c) and (d) (presentation of extra claims)

NOTE: Because additional fee for excess or multiple dependent claims not paid on filing or on later presentation must only be paid or these claims cancelled by amendment prior to the expiration of the time period set for response by the PTO in any notice of fee deficiency [37 CFR 1.16(d)], it might be best not to authorize the PTO to charge additional claim fees, except possibly when dealing with amendments after final action.

☒ 37 C.F.R. 1.16(e) (surcharge for filing the basic filing fee and/or declaration on a date later than the filing date of the application)

☒ 37 C.F.R. 1.17 (application processing fees)

WARNING: While 37 CFR 1.17(a), (b), (c) and (d) deal with extensions of time under § 1.136(a), this authorization should be made only with the knowledge that: "Submission of the appropriate extension fee under 37 C.F.R. 1.136(a) is to no avail unless a request or petition for extension is filed." (Emphasis added). Notice of November 5, 1985 (1080 O.G. 27).

☐ 37 C.F.R. 1.18 (issue fee at or before mailing of Notice of Allowance, pursuant to 37 C.F.R. 1.311(b))

NOTE: Where an authorization to charge the issue fee to a deposit account has been filed before the mailing of a Notice of Allowance, the issue fee will be automatically charged to the deposit account at the time of mailing the notice of allowance. 37 CFR 1.311(b).

NOTE: 37 CFR 1.28(b) requires "Notification of any change in loss of entitlement to small entity status must be filed in the application...prior to paying, or at the time of paying...issue fee." From the wording of 37 CFR 1.28(b): (a) notification of change of status must be made even if the fee is paid as "other than a small entity" and (b) no notification is required if the change is to another small entity.

16. Instructions as to Overpayment

☒ Credit Account No. 50-0270.

☐ Refund

Reg. No. 41,270

Tel. No. (972) 894-4959

Brian T. Rivers
Signature of Attorney

Brian T. Rivers

(Type or print name of attorney)

Nokia Inc.

6000 Connection Drive

(P. O. Address)

Irving, TX 75039

☐ **Incorporation by reference of added pages**

[check the following item if the application in this transmittal claims the benefit of prior U.S. application(s) (including an International Application entering the U.S. stage as a continuation, divisional or C-I-P application) and complete and attach the ADDED PAGES FOR NEW APPLICATION TRANSMITTAL WHERE BENEFIT OF PRIOR U.S. APPLICATION(S) CLAIMED.]

- ☐ Plus Added Pages for New Application Transmittal Where Benefit of Prior U.S. Application(s) Claimed

Number of pages added _____

- ☐ Plus Added Pages for Paper Referred to in Item 4 Above

Number of pages added _____

- ☐ Plus "Assignment Cover Letter Accompanying New Application"

Number of pages added _____

☐ **Statement Where No Further Pages Added**

(if no further pages form a part of this Transmittal, then end this transmittal with this page and check the following item)

- ☒ This transmittal ends with this page.

Patent Application Papers of: Qizheng Gu

Attorney Docket NO. NC29176

CDMA RECEIVER

FIELD OF THE INVENTION

The present invention relates generally to code division multiple access
5 (CDMA) receivers, and more particularly, to a method and apparatus for receiving multi-carrier (MC) CDMA signals that allows efficient implementation of a CDMA receiver in CDMA systems having multiple modes of operation.

BACKGROUND OF THE INVENTION

FIG. 1 shows a cellular system 100. The cellular system 100 coverage
10 area may be divided into separate areas defined by cells 101-107. Each mobile station 120-122 may operate within the coverage area of cellular system 100. Each cell 101-107 is controlled by a radio frequency transmitting and receiving base station 111-117 that allows base station-to-mobile and reverse-link (mobile station to base station) channels to be established. The reverse-link and forward-
15 link channels provide paths for communication between mobile stations and an associated base station 111-117. Cellular system 100 may be implemented according to one of the many cellular system standards currently in use or proposed for use. For example, system 100 may be implemented in accordance with the Telecommunications Industry Association standard (TIA/EIA) IS-95
20 Mobile Station-Base Station Compatibility Standards for Dual-Mode Wideband Spread Spectrum Cellular System ("IS-95") or in accordance with the Japanese Association of Radio Industries and Businesses (ARIB) standard Specification of Mobile Station for 3G Mobile Station System Version 1.0 (WCDMA) or other third-generation (3G) standards, such as the European multi-carrier CDMA (MC-
25 CDMA) or TIA/EIA cdma2000 First Generation Standard (cdma-2000_1x).

In cellular system 100, a number of forward-link CDMA channels can share the same time-frequency space. Similarly, a number of reverse-link channels can share another time-frequency space. To enable this time-frequency sharing, CDMA channels are separately defined by performing an orthogonal conversion
30 and spreading of information to be transmitted on the channel using Walsh codes.

Walsh codes can be used to uniquely spread channel information in the same time-frequency space used by other channels using different Walsh codes. At a receiver, the unique Walsh code assigned to a particular channel is used to despread a received signal and to discriminate the desired channel from others occupying the same time-frequency space. The technique is also referred to as "spread spectrum" communication.

To receive and despread CDMA channels that are modulated in a particular radio frequency (RF) band (i.e., a particular frequency space), a mobile station down-converts the carrier frequency of a received RF band and provides the down-converted signal to one or more fingers of a RAKE receiver (also referred to as "finger" receiver). A RAKE receiver contains despreading correlators that can despread a particular channel using the Walsh code associated with that channel. A RAKE receiver may employ multiple fingers to improve multipath signal reception. Different dominant multipath components of a multipath signal can be despread by different RAKE receiver fingers. The RAKE receiver may then combine the despread signals from the different multipath components to maximize the despread energy. The RAKE receiver may combine the despread signals based on an estimate of phase and amplitude of the despread components.

In a second-generation cellular phone system, such as an IS-95 CDMA system, digitized information is transmitted from a base station to multiple mobile stations using a single 1.23 MHz RF band that contains multiple CDMA forward-link channels. Similarly, digitized information from multiple mobile stations are transmitted to a base station over another 1.23 MHz RF band that contains multiple CDMA reverse-link channels.

More recently, third-generation broadband CDMA systems have been proposed in which forward-link spectrum is frequency subdivided into multiple RF bands. Within each of the RF bands, a different set of CDMA channels may be transmitted, where the CDMA channels in one RF band need not use mutually orthogonal coding in relation to another RF band. Third-generation CDMA cellular phone systems can implement an optional operation mode in which a high

capacity data channel may be formed between a base station and a mobile station by using multiple CDMA channels, each of which is in a different one of the RF bands. This optional mode may be referred to as multi-carrier (MC) mode.

As shown in FIG. 2, in a multi-carrier CDMA (MC-CDMA) system, data may
5 be transmitted from a base station to a mobile station using a 3.75 MHz of signal spectrum that is subdivided by frequency into different RF bands 211-213. Each of the RF bands 211-213 occupies its own RF spectrum and has a distinct carrier frequency, f_{c1} , f_{c2} , f_{c3} . In proposed MC-CDMA standards, each RF band 211-213 occupies a 1.25 MHz spectrum and adjacent carrier frequencies f_{c1} , f_{c2} , f_{c3} of the
10 RF bands have a minimum frequency spacing of 1.25 MHz. The carriers f_{c1} , f_{c2} , f_{c3} may be RF carriers in the cellular band (869-894 MHz) or in PCS band (1930-1990 MHz). Other carrier frequencies may also be used depending on available spectrum.

FIG. 3 shows a block diagram of a single-mode receiver, according to an
15 embodiment of the invention, that can be used in a single-mode MC-CDMA mobile station or base station to simultaneously receive and decode CDMA channels in different RF bands. The receiver 300 receives a radio frequency (RF) MC-CDMA signal (an "RF MC-CDMA" signal) from antenna 301 (which may be coupled to receiver 300 through duplexer 302) and provides decoded data to other circuitry in
20 the mobile station or base station on outputs 331-333. For example, outputs 331-333 may be coupled to an audio decompression circuit or a data storage device.

The receiver 300 includes an initial amplification stage 303 to amplify the relatively weak RF MC-CDMA signal received by antenna 301. The amplification stage 303 may include low noise amplifiers (LNAs), band pass filters (BPFs) and
25 radio frequency amplifiers (RFAs) that operate over a broad range of RF frequencies. An intermediate frequency MC-CDMA signal (an "IF MC-CDMA" signal) is then formed by down-converting the amplified RF MC-CDMA signal using a down-converter 304 (also known as a "signal mixer" or "mixer"). The down-converter 304 reduces the carrier frequencies f_{c1} , f_{c2} , and f_{c3} , of received RF
30 bands 211-213 (FIG. 2) by the frequency f_{LO} of a local oscillator 305 signal. As a result, the carrier frequencies f_{c1} , f_{c2} , and f_{c3} of the RF bands 211-213 are reduced

to intermediate frequency (IF) carriers f_{IF1} , f_{IF2} , and f_{IF3} , respectively, where
 $f_{IF1}=f_{c1}-f_{LO}$, $f_{IF2}=f_{c2}-f_{LO}$, and $f_{IF3}=f_{c3}-f_{LO}$. The resulting IF MC-CDMA signal is then
coupled through a band pass filter 306 and a variable gain amplifier 307. The
bandwidth of the band pass filter 306 is approximately equal to the bandwidth of
5 the three IF MC-CDMA bands (e.g., approximately 3.7 MHz total).

An I/Q quadrature mixer stage 350 is then used to down-convert the
amplified IF MC CDMA signal to produce an amplified and filtered base band
signal from the IF MC CDMA signal. The I/Q quadrature mixer stage 350 down-
converts the IF MC-CDMA signal to quadrature base band (BB) "I" and "Q" signals
10 using down-converters 308 and 309. Down-converters 308 and 309 reduce the
carrier frequencies of the IF MC-CDMA signal by the frequency f_{LO2} of another
local oscillator 320. The local oscillator frequency f_{LO2} may be equal to the
intermediate carrier frequency, f_{IF2} , of the channel 112. Frequency folding occurs
due to down-conversion using a local oscillator frequency $F_{LO2} = F_{IF2}$. As a result,
15 each down-converter 308 and 309 will output a base band (BB) MC-CDMA signal
having a bandwidth of approximately 1.875 MHz.

Frequency folding at down-converters 308 and 309 can result in the
corruption of the information spectrum. Within the I/Q quadrature mixer stage
350, loss of information is prevented by forming and separating I and Q channel
20 information. This can be accomplished by phase-shifting the local oscillator signal
used for down-conversion at down-converter 308 by $\pi/2$ radians with respect to
the oscillator signal used at 309. The resulting base band (BB) I and Q signals
are then amplified, filtered, and recombined to reconstruct the data and thus
contain the modulated spread CDMA data received in the three RF bands 211-
25 213.

Amplification and filtering of baseband I and Q signals is performed using
circuitry 310-313 and 314-317, respectively. Undesired high frequency
components in the BB I signal from down-converter 308 are attenuated using a
low pass filter 310. To minimize undesired signals, the low pass filter 310 should
30 have a cutoff frequency approximately equal to the bandwidth of the BB I signal
(e.g., 1.875 MHz). The filtered BB I signal is then amplified by amplifier 311 and

digitally sampled at analog-to-digital converters (ADC) 312. ADC 312 forms a digital representation of the BB I signal. In general, the ADC 312 will sample the BB I signal at a rate of at least twice the BB I signal's highest frequency (resulting, in this example, in a minimum sampling rate of 3.75 MHz). The digital representation of the BB I signal may be filtered again by a digital low pass filter 313 with a 1.875 MHz bandwidth to further remove any residual high frequency interference signals or undesired signals introduced by amplification or analog-to-digital conversion. The BB Q signal may be similarly processed by circuit elements 314-317.

The digitized representations of the BB I and BB Q signals are then summed together using a complex number summing circuit 318. Summing the BB I and BB Q signals results in a full bandwidth (e.g., 3.75 MHz) unfolded signal that contains three base-band signals, each of which corresponds to one of the original three RF bands 211-213. The three base band signals are then separated from each other by a digital filter bank 319 and provided to different RAKE receiver fingers 321-323. The fingers 321-323 can each despread a CDMA channel from its corresponding base band signal to produce digital output 331-333, respectively.

In general, the bandpass filters and low pass filter used in the MC-CDMA receiver architecture 300 are limited to, or optimized for, performance in a single mode (e.g., MC-CDMA). It may, however, be desirable to build a mobile station or other receiving apparatus that can operate in multiple modes. For example, a receiver that can operate in both MC-CDMA mode and IS-95 may be desirable. Referring to FIGs. 3 and 4, to adapt the single-mode receiver 300 for use in multiple modes, filters 306, 310, 313, 314, 317 in receiver 300 may each be replaced with a pair of switched filters (406A, 406B), (410A, 410B), (413A, 413B), (414A, 414B), (417A, 417B), respectively. The first filter in each pair (the "A" filter) may be used to receive a 3.85 MHz MC-CDMA signal and may have a filter value equal to the corresponding filter in receiver 300. The second filter in each pair (the "B" filter) may have a filter value used for filtering a 1.23 MHz IS-95 RF band. For example, filter 406B may be a 1.23 MHz band-pass filter, and filters 410B, 414B, 413B, 417B may each be 0.65 MHz low pass filter. In addition, oscillators 405 and 420 are frequency-selectable to conform to the particular transmission

frequencies used in each mode. The use of multiple filter sets to receive different types of CDMA signals may increase the complexity, cost, and/or power use of the receiver 400 or may have other disadvantages. Consequently, alternate receiver designs are desired. As third-generation systems are implemented, initial
5 coverage may be limited. Consequently, a mobile station that can transmit and receive second-generation CDMA signals as well as third-generation CDMA signals is desirable. Multi-mode receivers may require additional filtering, switching, and amplification circuitry that is mode-specific to implement multiple modes. This additional circuitry may add additional size, cost, and complexity to
10 the receiver. Consequently, it is desirable to have a flexible receiver design in which mode-specific circuitry is reduced.

SUMMARY OF THE INVENTION

The present invention provides a method and apparatus for receiving multi-carrier CDMA signals that allows efficient implementation of a CDMA receiver in
15 CDMA systems having multiple modes of operation. The invention utilizes multi-tone down conversion within a CDMA receiver operating in a multi-carrier mode.

Use of multi-tone down conversion in the receiver allows the number of components required to process a multi-carrier (MC) CDMA signal to be reduced and furthers efficient design of CDMA receivers operating in multiple modes, such
20 as an MC-CDMA/CDMA receiver that may include, for example, a TIA/EIA cdma2000 first generation (cdma2000_1x) mode.

In general, in one aspect, the invention features a signal reception method. The method includes receiving a signal, down-converting the received signal to form an intermediate signal through multi-tone down conversion, and decoding the
25 intermediate signal to extract data. The received signal may include multiple transmission bands, each of which occupies a different portion of a spectrum. Each of the transmission bands also includes an information channel signal. When the received signal is down-converted, the intermediate signal is formed. The intermediate signal may include signals from a common intermediate band
30 that includes an information channel from each of a plurality of different

transmission bands. When the intermediate signal is decoded, data from the plurality of information channels is extracted.

- In general, in another aspect, the invention features a signal reception apparatus. The apparatus includes a down-converter that is configured to form an
- 5 intermediate signal by down-converting a plurality of transmission bands to a common intermediate band through multi-tone conversion. Each transmission band includes a time period and spectrum portion shared by a group of channels. All of the the plurality of groups of channels share the common intermediate band. The apparatus also includes decoding circuitry coupled to the down-converter.
- 10 The decoding circuitry is configured to extract data from the common intermediate band. The extracted data include each of the plurality of groups of channels.

- Implementations may include one or more of the following features.
- Information channels may each include spread spectrum data. Each channel may use a different spreading code to spread its data. The transmission bands may
- 15 each be modulated using a different carrier frequency, and the intermediate signal may have a lower carrier frequency than the transmission bands. Down-converting may include using an oscillator signal having multiple frequencies. The multiple frequencies may have the same frequency spacing as a spacing between carrier frequencies in the transmission bands. A base band signal may be formed
- 20 by down-converting the common spectrum of the intermediate signal to a lower frequency second common spectrum. This second common spectrum may include the plurality of information channel signals. The base band signals may be spectrum folded and have a spectrum narrower than that of the intermediate signal. Multiple base band signals may be sampled and the samples may be
- 25 combined to form a full spectrum unfolded signal. The method may be implemented in a cellular mobile station or in a base station or in another receiving device. The method may also include amplifying and filtering of the received intermediate and/or base band signals. Each of the transmission bands may also include other information channels that are spread using other spreading codes.

- 30 In an embodiment, multi-tone down conversion is utilized to implement an MC-CDMA/CDMA receiver. In CDMA mode, including a cdma2000_1x mode, the

receiver receives a 1.23 MHz bandwidth signal at a carrier frequency. In MC-CDMA mode, the receiver receives three separate 1.23 MHz bandwidth signals that occupy a total bandwidth of approximately 3.75 MHz using three separate carrier frequencies. A down-converter is implemented that down-converts the received signal in CDMA mode by a single frequency. In MC-CDMA mode the down-converter down-converts the received signal by three frequencies. The frequencies used in down-converting are chosen so that the intermediate frequency band formed by the down-converting may pass through a bandpass filter having a 1.23 MHz bandwidth. In CDMA mode the signal passed through the bandpass filter is the received 1.23 MHz bandwidth signals. In MC-CDMA mode the intermediate signal passed through the bandpass filter is a composite of the three separate 1.23 MHz bandwidth signal. The intermediate signal is then processed through a baseband conversion stage. The output of the baseband stage is then simultaneously processed in a set of RAKE receiver fingers. In MC-CDMA mode each of the three received signals may be selected and despread using a Walsh code unique to each of the three received signals. In CDMA mode the RAKE fingers may be used to decode different dominant multipath components. Additionally, added RAKE fingers may be used to enable multipath decoding in MC-CDMA mode.

Implementations may include one or more of the following advantages. A receiver can operate to receive multiple signal types, such as IS-95, 3G_3x, and 3G_1x signals. A common set of intermediate frequency (IF) band pass filters (BPFs) and base-band (BB) low pass filters (LPFs) may be used for operation in different modes. This may reduce cost and part size compared with devices using different sets of intermediate filters and base band filters for different modes of operation.

BRIEF DESCRIPTION OF DRAWINGS

The details of one or more embodiments of the invention are set forth in the accompanying drawings and the description below. Other features, objects, and advantages of the invention will be apparent from the description and drawings, and from the claims.

FIG. 1 is a diagram of a conventional cellular radio communication system;

FIG. 2 shows different RF bands of a conventional cellular system;

FIG. 3 is a block diagram of a prior art single-mode receiver design;

FIG. 4 is a block diagram of a prior art multimode receiver design;

5 FIG. 5 is a block diagram of a multimode receiver design according to an embodiment of the invention;

FIG. 6 illustrates signal inputs and outputs within the receiver of FIG. 5;

FIG. 7 is a diagram illustrating signals in the receiver of FIG. 5;

FIG. 8 is a circuit diagram of oscillator 505 of the receiver of FIG. 5; and

10 FIG. 9 is a block diagram of a multimode receiver designed according to another embodiment of the invention.

DETAILED DESCRIPTION OF THE INVENTION

FIG. 5 is a block diagram of multimode receiver 500 according to an embodiment of the invention. Receiver 500 may support multiple operational
15 modes (for example, MC-CDMA and IS-95 modes). Receiver 500 supports multimode operation using a unique down-conversion mechanism that allows a wide bandwidth signal to be filtered, amplified and/or otherwise processed using common circuitry compatible with both a wide and a narrower bandwidth signal. More particularly, the receiver 500 has a single carrier mode in which the receiver
20 500 receives and despreads a CDMA channel transmitted in a single RF band (such as an IS-95 signal), and a multi-carrier mode in which the receiver 500 simultaneously receives and despreads multiple CDMA channels from different RF bands (e.g., bands 211-213 of FIG. 2).

25 An exemplary IS-95/MC-CDMA implementation is described to further explain the operation of the receiver 500. In the description that follows, IS-95 mode refers to a single-carrier mode in which a single IS-95 RF band having a 1.23 MHz bandwidth signal is received, and MC-CDMA mode refers to a multi-carrier mode in which three separate CDMA channels in three separate RF bands

211-213 of an MC-CDMA signal are received. The three bands 211-213 occupy a total bandwidth of approximately 3.75 MHz (1.25 MHz per band).

In both IS-95 and MC-CDMA modes, a relatively weak radio frequency (RF) signal from antenna 501 is amplified using an initial amplification stage 503.

- 5 Amplification stage 503 operates similar to amplification stage 303 (FIG. 3). Filters and amplifiers in the amplification stage 503 are compatible with the RF spectrum and bandwidth of both the IS-95 and MC-CDMA RF signals. Thus, for example, the pass-band of filters in the amplification stage 503 includes the spectrum occupied by the IS-95 RF band and by the MC-CDMA RF bands. The
- 10 amplified IS-95 or MC-CDMA RF signal is then coupled to a down-converter 504.

- Down-converter 504 reduces the carrier frequencies of RF bands by the frequencies produced by local oscillator 505. In IS-95 mode, local oscillator 505 operates in a single-tone mode wherein a single-frequency, f_{LO} , is output. When the local oscillator signal f_{LO} is mixed with the amplified IS-95 RF band from
- 15 amplifier stage 503, the carrier frequency of the IS-95 RF band is reduced by the frequency f_{LO} , thus forming an intermediate frequency (IF) IS-95 band having a 1.25 MHz bandwidth. In MC-CDMA mode, local oscillator 505 operates in a multi-tone mode, wherein a signal f_{LO-M} having multiple frequency components is output.

- Referring to FIG. 6, therein are illustrated signal inputs and outputs within
- 20 the receiver 500 in MC-CDMA mode. Local oscillator 505 outputs a local oscillator signal f_{LO-M} , 605, having three frequency components f_{LO3} , f_{LO2} , f_{LO1} . In general, the frequencies f_{LO3} , f_{LO2} , f_{LO1} will have the same spacing as carrier frequencies in the MC-CDMA RF bands 603 received from amplification stage 503. Thus, if the carrier frequencies f_{c3} , f_{c2} , f_{c1} of the MC-CDMA RF signal 603 have a spacing of
- 25 1.25 MHz, the frequencies f_{LO3} , f_{LO2} , f_{LO1} of the local oscillator signal 605 will, likewise, have a 1.25 MHz spacing.

- When a three band RF MC-CDMA signal 603 is down-converted at down-converter 504 using multi-tone local oscillator signal 605, the signal output by down-converter 504 will be a composite of the signal 603 carrier reduced by each
- 30 of the frequencies f_{LO3} , f_{LO2} , f_{LO1} . That is, each of the bands 211-213 will appear in the down-converter output three times – the first time with its carrier frequency

reduced by f_{LO1} , the second time with its carrier frequency reduced by f_{LO2} , and the third time with its carrier frequency reduced by f_{LO3} . This is illustrated in FIG. 7. In FIG. 7, the signal components resulting from down-converting bands 211, 212, and 213 using F_{LO-M} are shown, respectively, as 711, 712, and 713. The actual output of the down-converter is a composite of the signals 711-713. The composite signal output by the down converter 504 is shown as 704. As shown in 704, the three signals 711-713 each have one band in common [that is, the band with a carrier frequency $f_{ck-f_{LOk}}$ (for $k=1, 2, 3$)].

The composite signal 704 output by down-converter 504 is then filtered by a band pass filter 506 having a pass band of 1.23 MHz centered at the common carrier frequency $f_{ck-f_{LOk}}$ of the signal components 711-713. The output of filter 506, shown as 606, will have a 1.23 MHz bandwidth and will be a composite of each of the original RF bands 211-213 carrier reduced to the intermediate carrier frequency $f_{ck-f_{LOk}}$. In the receiver 500, the single-tone local oscillator signal f_{LO} , and the multitone local oscillator signals f_{LO3} , f_{LO2} , f_{LO1} will, in general, be selected such that the intermediate frequency signal produced in single-carrier mode and the common carrier frequency $f_{ck-f_{LOk}}$ produced in multi-carrier mode are the same. This allows both the intermediate frequency band formed by the down-converter in single-carrier mode, and the composite band formed by the down-converter in multi-carrier mode to pass through the band pass filter 506.

In both single-carrier and multi-carrier modes, the intermediate signal output by the down-converter 504 is then converted to base band signals, amplified, filtered, and digitally sampled. As in the receiver 300, the intermediate signal is converted to BB I and Q signals using a pair of down-converters 508 and 509 in an I/Q quadrature mixer stage 550. As with down-converters 308 and 309 (FIG. 3), the down-converters 508 and 509 mix the intermediate signal with a local oscillator signal to produce a spectrum-folded output signal. In the present example, the intermediate frequency IS-95 signal or composite (606) MC-CDMA signal is folded to a bandwidth of approximately 0.615 MHz. Additionally, as with down-converters 308 and 309, the local oscillator signal used for down-conversion at down-converter 508 is phase shifted by $\pi/2$ radians with respect to the local oscillator signal used at down-converter 509. Circuitry 510-518 also operates

similarly to circuit elements 310-318, respectively. Note that the pass band of filters 510, 513, 514, 517 will, in general, be lower than the pass band of the corresponding filters 310, 313, 314, 317 in receiver 300 due to the correspondingly lower intermediate signal input to stage 550. For example, in an
5 IS-95/MC-CDMA implementation, the filters 510, 513, 514, 517 will each have a 0.615 MHz pass band.

Digital representations of the BB I and Q signals produced by analog-to-digital converters 512 and 516 and filtered by digital filters 513 and 517 are then summed in a complex number summing circuit 518 to produce a full bandwidth
10 unfolded signal. The unfolded signal is then provided to each receiver finger 521-523 of the RAKE receiver. In multi-carrier mode, the receiver fingers 521-523, may be configured to use different Walsh codes to select and despread different CDMA channels (e.g., CDMA channels that originated in different RF bands 211-213). Thus, using the orthogonal properties of Walsh codes, the receiver fingers
15 can separate different channels from the composite signal 606. Note that, in some implementations, the same Walsh codes may be used in different bands 211-213; however, the Walsh codes in different bands will have different encoding phases. In IS-95 mode, the receiver fingers 521-523 may be configured to use the same Walsh code to decode a single CDMA channel but may be used to
20 decode different dominant multipath components. An implementation may include additional receiver fingers of the RAKE receiver to enable multipath decoding in multi-carrier mode.

FIG. 8 shows additional details of the local oscillator 504 that may be used to produce both a single-frequency local oscillator signal f_{LO} and a multi-frequency
25 local oscillator signal f_{LO-M} . The oscillator 505 may include a dual frequency synthesizer chip 801, a UHF voltage control oscillator (VCO) 802, a 1.25 MHz frequency oscillator 803, a UHF mixer 804, buffers 805-808, and a signal combiner 809. The 1.25 MHz oscillator, mixer, buffers, and combiner can be integrated in a monolithic integrated circuit (IC) with the synthesizer chip, or a
30 receiver RF or IF chip. The three-tone synthesizer has two operation modes. One generates three UHF tones and another one performs as a conventional synthesizer providing only single tone. The frequency interval between two

adjacent tones is 1.25 MHz, and output power level of each tone is around 0 ~ 5 dBm.

Although a multi-carrier mode using three RF bands was described, implementations may use a greater or fewer number of RF bands in multi-carrier mode and local oscillator 505 producing a greater or fewer number of frequencies. Additionally, an implementation may down-convert the multiple RF bands such that only a subset of RF bands overlap. For example, the number of RF bands in a multi-carrier system may be expanded to six and the local oscillator 505 may be configured to produce an oscillator signal containing two corresponding frequencies.

Referring to FIG. 9, an exemplary six-band receiver 900 is shown. The receiver 900 receives an RF signal that includes six RF bands. Each of the RF bands may occupy a 1.23 MHz bandwidth and the carrier frequencies of the six bands may be spaced 1.25 MHz apart. In addition, the desired CDMA signals in the first three adjacent RF bands may all use the same Walsh code (code A), while the desired CDMA signals in the second three adjacent RF bands may all use another Walsh code (code B).

Receiver 900 down-converts the six bands in the received RF signal to a three-band intermediate signal by mixing the six-band signal with a local oscillator signal containing two frequencies in mixer 904. The two local oscillator frequencies may be spaced three carrier frequencies (3.70 MHz) apart. Thus, the three bands in the resulting intermediate frequency signal will be formed by overlapping the first three adjacent RF bands with the second three adjacent bands. Thus, each of the intermediate bands will contain a desired CDMA channel using Walsh code "A" and another desired channel using Walsh code "B". The three bands in the intermediate signal may then be processed using circuit elements 906-920. Circuitry 906-920 may be substantially identical to circuitry 306-320 (FIG. 3). Thus, each of the three outputs from the digital filter 919 will consist of a different one of the three intermediate frequency bands. These three separated bands, each containing a Walsh code "A" CDMA signal and a Walsh code "B" CDMA signal, are provided to a different pair of receiver fingers 921-926.

Each pair of receiver fingers consists of a receiver (921, 923, 925) configured to decode Walsh code A, and another receiver finger (922, 924, 926) configured to decode Walsh code B.

A number of embodiments of the present invention have been described.

- 5 Nevertheless, it will be understood that various modifications may be made without departing from the spirit and scope of the invention. For example, a different number of initial and intermediate amplification and filtering stages may be used. Accordingly, other embodiments are within the scope of the following claims.

What is claimed is:

- 1 1. A method for receiving a signal, said method comprising the steps
2 of:
3 receiving an RF signal, said RF signal comprising a plurality of
4 information channel signals, wherein each of said plurality of
5 information channel signals are transmitted in one of a plurality of
6 transmission bands, and each of said plurality of information channel
7 signals is carried on one of a plurality of carrier frequencies;
8 down-converting said RF signal to form an intermediate signal,
9 wherein said intermediate signal comprises down-converted versions
10 of each of said plurality of information channel signals, and said
11 down-converted versions of each of said plurality of information
12 channel signals are within a common frequency spectrum; and
13 decoding said intermediate signal to extract data from said down-
14 converted versions of each of said plurality of information channel
15 signals.
1 2. The method of claim 1, wherein said plurality of information channel
2 signals each comprises different code division multiple access data.
1 3. The method of claim 2, wherein each of said plurality of information
2 channel signals comprises data spread using at least one spreading code.
1 4. The method of claim 3, wherein each of said plurality of information
2 channel signals is spread by different spreading codes.
1 5. The method of claim 1, wherein said step of down-converting
2 comprises down-converting each one of said plurality of carrier frequencies by a
3 plurality of oscillator frequencies.
1 6. The method of claim 5, wherein the frequency spacing between
2 each adjacent pair of said plurality of carrier frequencies and between each
3 adjacent pair of said oscillator frequencies is substantially the same.

1 7. The method of claim 1, wherein said common frequency spectrum
2 comprises a first common frequency spectrum, and the step of decoding said
3 intermediate signal comprises the step of forming a base band signal by down-
4 converting said first common frequency spectrum to a second common frequency
5 spectrum, said second common frequency spectrum lower in frequency than said
6 first common frequency spectrum.

1 8. The method of claim 7, wherein the step of forming said base band
2 signal further comprises down-converting the intermediate signal using a first
3 oscillator signal to form a first base band component signal and a second
4 oscillator signal to form a second base band component signal, the first and
5 second oscillator signals each at a same frequency and a different phase.

1 9. The method of claim 8, wherein said first base band component
2 comprises a first folded signal and said second base band component comprises
3 a second folded signal, each folded signal having a frequency spectrum narrower
4 than said first common frequency spectrum.

1 10. The method of claim 9 further comprising the steps of:
2 sampling said first base band component to form a first digital
3 representation;
4 sampling said second base band component to form a second digital
5 representation; and
6 combining said first and said second digital representations to form
7 an unfolded signal, said unfolded signal having a frequency
8 spectrum greater than the spectrum of the first folded signal.

1 11. The method of claim 1, wherein the step of receiving an RF signal
2 comprises receiving an RF signal from a cellular radio base station.

1 12. The method of claim 1, further comprising the step of filtering said
2 intermediate signal to attenuate at least one signal outside the common frequency
3 spectrum before performing said step of down-converting.

1 13. A mobile radio telephone unit comprising:

an antenna configured to receive an RF signal, said RF signal comprising a plurality of information channel signals, wherein each of said plurality of information channel signals is transmitted in one of a plurality of transmission bands, and each of said plurality of information channel signals is carried on one of a plurality of carrier frequencies;

a down-converter operatively coupled to the antenna and configured to down-convert said RF signal to form an intermediate signal, wherein said intermediate signal comprises down-converted versions of each of said plurality of information channel signals, and said down-converted versions of each of said plurality of information channel signals are within a common frequency spectrum;

a decoder operatively coupled to the down-converter and configured to decode said intermediate signal to extract data from said down-converted versions of each of said plurality of information channel signals.

14. The apparatus of claim 13, wherein each of said plurality of information channel signals comprises different code division multiple access data, and each of said information channel signals comprises data spread using at least one spreading code.

15. The apparatus of claim 13, wherein said down-converter is configured to down-convert each of said plurality of carrier frequencies by a plurality of carrier frequencies having a lower frequency.

16. The apparatus of claim 13, wherein said down-converter comprises an oscillator for generating an oscillator signal comprising a plurality of oscillator frequencies, the frequency spacing between each adjacent pair of said plurality of carrier frequencies and between each adjacent pair of said plurality of oscillator frequencies being substantially the same.

1 17. The apparatus of claim 15, wherein the decoder comprises a CDMA
2 decoder configured to extract data from said down-converted version of each of
3 said plurality of information channel signals using a different despreading code.

1 18. A signal reception apparatus comprising:

2 a down-converter configured to form an intermediate signal by down-
3 converting an RF signal including a plurality of transmission bands to
4 at least one intermediate band, said at least one intermediate band
5 including at least one channel, wherein said down-converter down-
6 converts by multiplying said RF signal by at least two frequencies;
7 and

8 decoding circuitry coupled to the down-converter and configured to
9 extract data from each at least one intermediate band, wherein the
10 extracted data comprises data from each at least one channel
11 included in each at least one intermediate band.

1 19. The apparatus of claim 18, wherein each of the at least one
2 channels of each at least one intermediate band comprises a different spread
3 spectrum signal, and wherein the decoding circuitry comprises a spread spectrum
4 decoder to extract data from the intermediate band using a spreading code
5 associated with each at least one channel of each at least one intermediate band.

1 20. A CDMA receiver for operating in at least a first mode and a second
2 mode, said CDMA receiver comprising:

3 an initial RF stage, said initial RF stage for outputting a received RF
4 signal;

5 an oscillator, said oscillator for generating a plurality of oscillator
6 signals, each at a different frequency, when the receiver operates in
7 the first mode and generating a single oscillator signal when the
8 receiver operates in the second mode;

9 a down-converter coupled to said initial RF stage and said oscillator,
10 said down-converter for receiving said received RF signal and

11 multiplying said RF signal by said plurality of oscillator signals when
12 the receiver operates in the first mode, and multiplying said RF
13 signal by said single oscillator signal when the receiver operates in
14 the second mode, to generate an intermediate signal; and
15 a base band stage, coupled to said down-converter, said base band
16 stage for processing said intermediate signal.

ABSTRACT

A signal reception method including method and apparatus for receiving a signal, down converting the received signal through multi-tone down conversion to form an intermediate signal, and decoding the intermediate signal to extract data. In an embodiment, the received signal may include multiple transmission bands of a multi-code (MC)- CDMA signal, each of which occupies a different spectrum. Each of the transmission bands also includes an information channel signal. When the received MC-CDMA signal is down converted through multi-tone down conversion, the intermediate signal is formed. The intermediate signal includes a common spectrum that includes an information channel from a plurality of transmission bands. When the intermediate signal is decoded, data from a plurality of information channel bands is extracted. The method and apparatus may be implemented in a multi-mode MC-CDMA/CDMA receiver.




Fig. 1
(Prior Art)

662221-2837400




Fig. 2

Prior Art




Fig. 3

Prior Art




Fig. 4

$$P_{v\bar{c}v} A_v +$$




Fig. 5




Fig. 6




Fig. 7

504




Fig. 8




Fig. 9